

MA 2275

STEREO INTEGRATED AMPLIFIER

McIntosh
The Compendium



FRONT PANEL: Glass with LED/fiber-optic illuminated green/gold nomenclature. Left and right POWER OUTPUT meters (LINEAR WATTS or DECIBELS). 7 INPUT SELECTOR with indicator lights: PHONO, CD 2, CD, TUNER, DVD, TAPE. BASS. TREBLE. METER control: LIGHTS OFF, WATTS or HOLD. BALANCE. VOLUME. 7 HEADPHONES jack. IR sensor. Pushbutton switches: RECORD MONITOR (with indicator), TONE BYPASS, MONO, MUTE, STANDBY/ON (with indicator). TUBE WARMUP indicator. POWER: ON or OFF.



BACK PANEL: Polished stainless steel chassis. RIGHT channel OUTPUT binding posts for 2 Ω , 4 Ω or 8 Ω speakers. LEFT channel OUTPUT binding posts for 2 Ω , 4 Ω or 8 Ω speakers. 7 Jumper: POWER AMP input, PREAMP OUTPUTS 1. PREAMP OUTPUTS 2. TAPE OUTPUTS. INPUTS: TAPE, DVD, TUNER, CD, CD 2, and PHONO. Ground binding post. 7 Power cord receptacle. FUSE. Coax EXTERNAL SENSOR connector. POWER CONTROL output: MAIN and ACCESSORY. DATA PORTS: SUM, TAPE, DVD, TUNER, CD 2, CD, and PHONO. Balanced CD INPUT.

MA 2275

STEREO INTEGRATED AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 75w/ch into 2 ohms, 4 or 8 ohms. **Response:** 20-20kHz (+0 – 0.5dB). **Distortion:** 0.5%. **Noise and Hum:** 100dB power amp, -93dB high level, -80dB low level re 10mV. **Damping Factor:** greater than 18. **Input Sensitivity and Impedance:** high level 0.25V (8V max) at 22k, phono 2.5mV (90mV max) at 47k and 65pF. **Unity coupled.** **Power Requirements:** 120V at 3 Amps. Has hand remote **HR 2275**.

TUBES: 4-KT88/6550 output, 4-12AX7A, 2-12AT7. Solid state rectifier bridges.



MA 2275 - Sold from 2004 - 2011. S/N: VK1001~VK????

Size: 10-1/8"H, 17-3/4"W and 18-3/4"D. **Weight:** 77 lbs. **\$6,100.00**